

Contents

1. Description
 - 1.1 Background information
 - 1.2 Reagent and instrument requirements
2. Use of the MACSima Stain Support Kit with dissolved antibodies and MACSwell™ Deepwell Plates
 - 2.1 Preparation of the MACSwell Deepwell Plates
 - 2.2 Preparation of samples
 - 2.3 Loading the MACSima Imaging System
3. Use of the MACSima Stain Support Kit with dried antibodies on REAscreen™ Antibody Panels
 - 3.1 Preparation of samples
 - 3.2 Loading the MACSima Imaging System

Warnings

Reagents contain sodium azide. Under acidic conditions sodium azide yields hydrazoic acid, which is extremely toxic. Azide compounds should be diluted with running water before discarding. These precautions are recommended to avoid deposits in plumbing where explosive conditions may develop.

1. Description

This product is for research use only.

Components 1×1 mL DAPI Staining Solution
 1×1 mL FcR Blocking Reagent, human
 2×1 mL REAlease® Release Reagent
 2× MACSima Mixing Vials (empty)

Product format DAPI Staining Solution is supplied in distilled water at a concentration of 5 µg/mL. FcR Blocking Reagent and REAlease Release Reagent are supplied in buffer containing 0.05% sodium azide and stabilizer.

Storage Store protected from light at 2–8 °C. Do not freeze. The expiration date is indicated on the vial labels. Do not use after this date.

1.1 Background information

The MACSima Stain Support Kit is designed for use with the MACSima Imaging System. The MACSima Imaging System is a fully automated instrument capable of staining hundreds of markers on one sample using the MACSima Imaging Cyclic Staining (MICS) technology. The kit contains support reagents and mixing vials necessary to perform experiments with the MACSima Imaging System. DAPI Staining Solution is used to stain cell nuclei. FcR Blocking Reagent is used to block unwanted binding of antibodies to human Fc receptor-expressing cells such

as B cells, monocytes, and macrophages. REAlease Release Reagent is used for signal removal from samples stained with REAlease or REA_dye_lease™ Antibody Complexes.

1.2 Reagent and instrument requirements

- MACSima Imaging System (# 130-121-164).
- MACSima Running Buffer (# 130-121-565).
- MACSwell One Imaging Frames (# 130-124-673), MACSwell Two Imaging Frames (# 130-124-675), MACSwell Four Imaging Frames (# 130-124-676), or MACSwell 24 Imaging Plates (# 130-124-677).
- (Optional) Dissolved fluorochrome-conjugated antibodies. For more information about MICS-validated antibodies refer to www.miltenyibiotec.com.
- (Optional) MACSwell Deepwell Plates (# 130-126-865).
- (Optional) MACSwell Sealing Foils (# 130-126-866).
- (Optional) REAscreen Antibody Panels containing dried antibodies.

2. Use of the MACSima Stain Support Kit with dissolved antibodies and MACSwell Deepwell Plates

▲ Plan the experiment beforehand in the MACSima Software.

▲ Upon experiment planning, the MACSima Software will indicate the number of MACSima Stain Support Kits and further material needed. It will also indicate the volumes needed of each reagent for preparation of the final staining solutions in the individual wells of the MACSwell Deepwell Plates.

2.1 Preparation of the MACSwell Deepwell Plates

▲ For detailed information on MACSwell Deepwell Plates please refer to the respective data sheet.

1. Add MACSima Running Buffer into the MACSwell Deepwell Plate.
2. Add DAPI Staining Solution into the dedicated well positions on the MACSwell Deepwell Plate.
3. (Optional) Add FcR Blocking Reagent into the well positions on the MACSwell Deepwell Plate.

▲ **Note:** For REAfinity™/REAlease/REA_dye_lease Antibodies it is not required to add FcR Blocking Reagent.
4. Add the dissolved fluorochrome-conjugated antibodies at their respective final dilution into their dedicated well positions on the MACSwell Deepwell Plate and resuspend by manually pipetting up and down.
5. Seal the MACSwell Deepwell Plate with a MACSwell Sealing Foil. For this, carefully detach the protection film of the adhesive side holding the foil at the protected margin.

Accurately place the foil above the plate and attach it to the surface of the plate. Make sure all wells are covered.

▲ **Note:** MACSwell Deepwell Plates can only be sealed with MACSwell Sealing Foils due to requirements of the MACSima Imaging System.

2.2 Preparation of samples

1. Prepare sample(s) for the experiment as described in the respective MACSwell™ Imaging Frames data sheet and add the initial sample volume of MACSima Running Buffer to each well depending on the used MACSwell Imaging Frame:
1900 µL for MACSwell One,
950 µL for MACSwell Two, or
475 µL for MACSwell Four Imaging Frames or MACSwell 24 Imaging Plates.

▲ **Note:** Make sure that the initial sample volume is correct before loading the sample into the MACSima Imaging System.

2. In case of manual pre-staining of cell nuclei with DAPI prior to the MICS experiment, proceed with steps 3–6. If no manual pre-staining is performed, directly proceed with chapter 2.3.
3. (Optional) Prepare the pre-staining solution by diluting DAPI Staining Solution 1:5 for tissue sections and adherent cells, or 1:25 for suspension cells in MACSima Running Buffer with a final volume per well depending on the used MACSwell Imaging Frame:
1000 µL for MACSwell One,
500 µL for MACSwell Two, or
250 µL for MACSwell Four Imaging Frames or MACSwell 24 Imaging Plates.
- ▲ **Note:** The optimal dilution factor of DAPI Staining Solution may vary depending on the sample type and might need to be adjusted.
4. (Optional) Remove the MACSima Running Buffer from the sample(s) by pipetting. Add the pre-staining solution and incubate for 10 minutes in the dark at room temperature (19–25 °C).
5. (Optional) Remove the pre-staining solution and wash the sample(s) three times by adding MACSima Running Buffer to each well depending on the used MACSwell Imaging Frame:
1900 µL for MACSwell One,
950 µL for MACSwell Two, or
475 µL for MACSwell Four Imaging Frames.
6. (Optional) Add MACSima Running Buffer to each well depending on the used MACSwell Imaging Frame:
1900 µL using MACSwell One,
950 µL using MACSwell Two, or
475 µL using MACSwell Four Imaging Frames or MACSwell 24 Imaging Plates.

▲ **Note:** Make sure that the initial sample volume is correct before loading the sample into the MACSima Imaging System.

2.3 Loading the MACSima Imaging System

▲ Please refer to the MACSima Imaging System user manual for detailed information on how to use the instrument.

1. Start the MACSima Imaging System and software.
2. Refer to the user manual and follow the instructions of the MACSima Software.

3. Load the respective experiment configuration.
4. Load the MACSwell Deepwell Plate sealed with a MACSwell Sealing Foil, the components of the MACSima Stain Support Kit, and the MACSwell Imaging Frame(s) or Plate containing the prepared sample(s) into the instrument as instructed by the MACSima Software.

▲ **Note:** Be sure to load the plates in the correct orientation.

▲ **Note:** Remove the lids of the reagent vials and ensure that the MACSima Mixing Vials are open and empty before placing them into the instrument.

5. Start the experiment by following the instructions of the MACSima Software.
6. After the experiment has finished, follow the instructions of the MACSima Software. Discard the MACSwell Deepwell Plate and the reagent vials.

3. Use of the MACSima™ Stain Support Kit with dried antibodies on REAscreen™ Antibody Panels

▲ Plan the experiment beforehand in the MACSima Software.

▲ Upon experiment planning, the MACSima Software will indicate the material needed.

3.1 Preparation of samples

1. Prepare sample(s) for the experiment as described in the respective MACSwell Imaging Frames data sheet and add the initial sample volume of MACSima Running Buffer to each well depending on the used MACSwell Imaging Frame:
1900 µL for MACSwell One,
950 µL for MACSwell Two, or
475 µL for MACSwell Four Imaging Frames or MACSwell 24 Imaging Plates.

▲ **Note:** Make sure that the initial sample volume is correct before loading the sample into the MACSima Imaging System.

2. In case of manual pre-staining of cell nuclei with DAPI prior to the experiment, proceed with steps 3–6. If no manual pre-staining is performed, directly proceed with chapter 3.2.
3. (Optional) Prepare the pre-staining solution by diluting DAPI Staining Solution 1:5 for tissue sections and adherent cells, or 1:25 for suspension cells in MACSima Running Buffer with a final volume per well depending on the used MACSwell Imaging Frame:
1000 µL for MACSwell One,
500 µL for MACSwell Two, or
250 µL for MACSwell Four Imaging Frames or MACSwell 24 Imaging Plates.
- ▲ **Note:** The optimal dilution factor of DAPI Staining Solution may vary depending on the sample type and might need to be adjusted.
4. (Optional) Remove the MACSima Running Buffer from the sample(s) by pipetting. Add the pre-staining solution and incubate for 10 minutes in the dark at room temperature (19–25 °C).
5. (Optional) Remove the pre-staining solution and wash the sample(s) three times by adding MACSima Running Buffer to each well depending on the used MACSwell Imaging Frame:
1900 µL for MACSwell One,
950 µL for MACSwell Two, or

475 µL for MACSwell Four Imaging Frames.

6. (Optional) Add MACSima Running Buffer to each well depending on the used MACSwell™ Imaging Frame:
1900 µL using MACSwell One,
950 µL using MACSwell Two, or
475 µL using MACSwell Four Imaging Frames or MACSwell 24 Imaging Plates.

▲ **Note:** Make sure that the initial sample volume is correct before loading the sample into the MACSima Imaging System.

3.2 Loading the MACSima™ Imaging System

▲ Please refer to the MACSima Imaging System user manual for detailed information on how to use the instrument.

1. Start the MACSima Imaging System and software.
2. Refer to the user manual and follow the instructions of the MACSima Software.
3. Load the respective experiment configuration.
4. Unpack the REAscreen™ Antibody Panel Plate(s) from the pouch.
▲ **Note:** Do not remove the sealing or add buffer to the REAscreen Antibody Panel Plate(s). The MACSima Imaging System will resuspend the antibodies automatically.
5. Load the REAscreen Antibody Panel Plate(s), the components of the MACSima Stain Support Kit, and the MACSwell Imaging Frame(s) or Plate containing the prepared sample(s) into the instrument as instructed by the MACSima Software.
▲ **Note:** Be sure to load the plate in the correct orientation.
▲ **Note:** Remove the lids of the reagent vials and ensure that the MACSima Mixing Vials are open and empty before placing them into the instrument.
6. Start the experiment by following the instructions of the MACSima Software.
7. After the experiment has finished, follow the instructions of the MACSima Software. Discard the REAscreen Antibody Panel Plate(s) and the reagent vials.

Refer to www.miltenyibiotec.com for all data sheets and protocols. Miltenyi Biotec provides technical support worldwide. Visit www.miltenyibiotec.com for local Miltenyi Biotec Technical Support contact information.

Legal notices

Limited product warranty

Miltenyi Biotec B.V. & Co. KG and/or its affiliate(s) warrant this product to be free from material defects in workmanship and materials and to conform substantially with Miltenyi Biotec's published specifications for the product at the time of order, under normal use and conditions in accordance with its applicable documentation, for a period beginning on the date of delivery of the product by Miltenyi Biotec or its authorized distributor and ending on the expiration date of the product's applicable shelf life stated on the product label, packaging or documentation (as applicable) or, in the absence thereof, ONE (1) YEAR from date of delivery ("Product Warranty"). Miltenyi Biotec's Product Warranty is provided subject to the warranty terms as set forth in Miltenyi Biotec's General Terms and Conditions for the Sale of Products and Services available on Miltenyi Biotec's website at www.miltenyibiotec.com, as in effect at the time of order ("Product Warranty"). Additional terms may apply. BY USE OF THIS PRODUCT, THE CUSTOMER AGREES TO BE BOUND BY THESE TERMS.

THE CUSTOMER IS SOLELY RESPONSIBLE FOR DETERMINING IF A PRODUCT IS SUITABLE FOR CUSTOMER'S PARTICULAR PURPOSE AND APPLICATION METHODS.

Technical information

The technical information, data, protocols, and other statements provided by Miltenyi Biotec in this document are based on information, tests, or experience which Miltenyi Biotec believes to be reliable, but the accuracy or completeness of such information is not guaranteed. Such technical information and data are intended for persons with knowledge and technical skills sufficient to assess and apply their own informed judgment to the information. Miltenyi Biotec shall not be liable for any technical or editorial errors or omissions contained herein.

All information and specifications are subject to change without prior notice. Please contact Miltenyi Biotec Technical Support or visit www.miltenyibiotec.com for the most up-to-date information on Miltenyi Biotec products.

Licenses

This product and/or its use may be covered by one or more pending or issued patents and/or may have certain limitations. Certain uses may be excluded by separate terms and conditions. Please contact your local Miltenyi Biotec representative or visit Miltenyi Biotec's website at www.miltenyibiotec.com for more information.

The purchase of this product conveys to the customer the non-transferable right to use the purchased amount of the product in research conducted by the customer (whether the customer is an academic or for-profit entity). This product may not be further sold. Additional terms and conditions (including the terms of a Limited Use Label License) may apply.

CUSTOMER'S USE OF THIS PRODUCT MAY REQUIRE ADDITIONAL LICENSES DEPENDING ON THE SPECIFIC APPLICATION. THE CUSTOMER IS SOLELY RESPONSIBLE FOR DETERMINING FOR ITSELF WHETHER IT HAS ALL APPROPRIATE LICENSES IN PLACE. Miltenyi Biotec provides no warranty that customer's use of this product does not and will not infringe intellectual property rights owned by a third party. BY USE OF THIS PRODUCT, THE CUSTOMER AGREES TO BE BOUND BY THESE TERMS.

Trademarks

MACSima, MACSwell, the Miltenyi Biotec logo, REAdey_{lease}, REAfinity, REAlease, and REAscreen are registered trademarks or trademarks of Miltenyi Biotec and/or its affiliates in various countries worldwide. All other trademarks mentioned in this publication are the property of their respective owners and are used for identification purposes only.

Copyright © 2021 Miltenyi Biotec and/or its affiliates. All rights reserved.